

# Metro

## Prepaid

SUB METERS FOR TENANTS

MET001 METRO DIGITAL PREPAID METER

# SINGLE PHASE

A single phase encryption enabled prepayment meter with PayPoint integrated vending of power codes.



## Technical Parameters

Wiring Mode	Rated Current (Ib)	Max. Current (Imax)
Single Phase Two-wire LNNL	5A	80A
Starting Current (0.4% Ib)	Rated Voltage (Un)	Working Voltage Range
20mA	230V	80% Un ~ 120%Un
Rated Frequency (fn)	Accuracy Class	Meter Constant
50Hz ± 5%	Active: IEC Class 1.0	Active: 1000imp/kWh
Voltage Circuit Power Consumption	Current Circuit Power Consumption	Working Temperature
≤2W 10VA	≤4VA	-25°C~70°C